

SOUND LEVEL METER

SL-1352



Performance with Precision



FEATURES :

- ☒ MEASURES & MANAGE SOUNDS FROM VARIETY OF SOURCES (MEASURES FROM 30dB ~ 130dB)
- ☒ 4 DIGIT LCD WITH A RESOLUTION OF 0.1dB
- ☒ MAX / MIN RECORD
- ☒ OVER RANGE / UNDER RANGE DISPLAY
- ☒ TIME, DATA TRANSMISSION DISPLAY
- ☒ A & C WEIGHTING
- ☒ SELECTABLE RESPONSE TIME : FAST / SLOW
- ☒ ANALOG AC/DC OUTPUTS FOR CONNECTION TO FREQUENCY ANALYZER OR X-Y SHAFT RECORDER.
- ☒ PC REAL TIME MONITORING, RECORDING & MEMORY
- ☒ DATA LOGGING FUNCTION
- ☒ ADJUSTABLE ALARM LEVELS
- ☒ AUTO POWER OFF
- ☒ METER MEMORY : 262100 READING
- ☒ DATA HOLD
- ☒ USB COMPUTER INTERFACE (ADVANCE SOFTWARE PROGRAM FOR ALL WINDOW)

SPECIFICATION

FREQUENCY RANGE	31.5Hz ~ 8kHz
RESOLUTION	0.1dB
ACCURACY	±1.4dB
DYNAMIC RANGE	50dB
MEASURING LEVEL RANGE	Low: 30dB~80dB
	Med: 50dB~100dB
	High : 80dB~130dB
	Auto: 30dB~130dB
TIME WEIGHTING	Fast : (125mS); Slow : (1s)
MICROPHONE	½ inch electret condenser microphone
ANALOG OUTPUT	AC/DC Output
DATA RECORDING	AC=1Vrms; DC=10V/dB
DISPLAY UPDATE	2 times/sec

POWER : 9V (6F22) x 1

Dimension	: H252 x W66x D33 mm
Weight	: Approx.
Accessories	: Main Unit, Hard Carrying Case, Wind Muffler, Screwdriver, USB Cable, Adaptor, Software, Tripod (Optional), User Manual
Qty	: 10 Pcs. in a Box.



Back light



Alarm



Low Battery
Indication



Auto Power Off



Over / Under Range
Display

FEATURES :

- ☒ 4 DIGIT LCD WITH A RESOLUTION OF 0.1dB
- ☒ MAX / MIN RECORD
- ☒ OVER RANGE / UNDER RANGE DISPLAY
- ☒ TIME, DATA TRANSMISSION DISPLAY
- ☒ A & C WEIGHTING
- ☒ SELECTABLE RESPONSE TIME : FAST / SLOW
- ☒ ANALOG AC/DC OUTPUTS FOR CONNECTION TO FREQUENCY ANALYZER OR X-Y SHAFT RECORDER.
- ☒ PC REAL TIME MONITORING, RECORDING & MEMORY
- ☒ DATA LOGGING FUNCTION
- ☒ ADJUSTABLE ALARM LEVELS
- ☒ AUTO POWER OFF
- ☒ METER MEMORY : 262100 READING
- ☒ DATA HOLD
- ☒ USB COMPUTER INTERFACE
(ADVANCE SOFTWARE PROGRAM FOR ALL WINDOW)
- ☒ MEMORY : 30 GROUPS WITH MEASURING CONDITION

For product demonstration visit the link below

<https://youtu.be/U4inzssE-js?si=VgdqFNQFy9Rfb9HE>

