

DIGITAL MULTIMETER MAS830L

APPLICATION: This is a 3½ Digits multimeter with Backlight. This instrument can be used to measure AC/DC Voltage, DC Current, Resistance, Diode, Continuity and other parameters. It is an ideal tool for the Electricians, Engineers, Laptop & Mobiles & Electronics appliances Repairing Centre, Factories, Industries, Laboratories, Students, Household.

FEATURES:

- Display: 3 ½ digit display with 1999 counts
- Over Range Indication: "1"
- Operating Temperature & Humidity: 0°C to 40°C < 75% RH
- Storage Temperature & Humidity: -10°C to 50°C < 75% RH
- Polarity Indication: Displayed for Negative Polarity
- Data hold Function
- Back Light
- Low Battery Indication
- Power supply: 9 Volt batteries
- Unit Size: 138 X 69 X 31 mm
- Display Size: 20x45mm
- Weight: Approx.170g. (Including Batteries)
- Accessories: Instruction Manual, 1 Set test leads & 1pc 9Volt battery.



SPECIFICATION:

Basic Function	Range	Best Accuracy
DC Current	200µA/2mA/20mA/200mA/10A (5 Ranges)	±1.5%
AC Voltage	20V0/600V (2 Ranges)	±1.2%
DC Voltage	200mV/2V/20V/200V/600V (5 Ranges)	±0.8%
Resistance	200Ω/2kΩ/20kΩ/200kΩ/2MΩ (5 Ranges)	±1.0%
Transistor HFE PNP & NPN	0~1000	
Diode	Yes	
Continuity	Yes	