

DIGITAL TRUE RMS MULTIMETER DT117

APPLICATION: This is a 3¾ Digits True RMS Multimeter with Backlight. This instrument can be used to measure AC/DC Voltage, AC/DC Current, Resistance, Capacitance, Frequency, Diode, Continuity Test, Non-Contact Voltage detection and other parameters. It is an ideal tool for the Electricians, Engineers & Factories, Industries, Laboratories, Students, Household.

FEATURES:

- Display: 3¾ Digits with 5999 Counts with Backlight.
- Over Range Indication,
- Overload Protection
- Data Hold Function
- Auto/Manual Range Selection Non-Contact AC Voltage Detector.
- Sampling Time 0.4 Seconds
- Auto Power off
- Operating Temperature & Humidity: 0°C To 40°C, <75%RH
- Storage Temperature & Humidity: -10°C To 50°C, <75%RH
- Power supply: 1 X 9 Volt Battery
- Display Size: 62 X 35 mm
- Dimension: 185×85×52mm
- Weight: 368gm Excluding Battery
- Accessories: Instruction Manual, 9V Battery, 1Set Test lead, 1 pc 9V Battery

SPECIFICATION:

Basic Function	Range	Best Accuracy
AC Current	10A (2 ranges μ A, mA, A)	\pm 3%
DC Current	10A (2 ranges μ A, mA, A)	\pm 2.0%
AC Voltage	750V (Auto Range)	\pm 1.5%
DC Voltage	1000V (Auto Range)	\pm 0.5%
Resistance	60M Ω (Auto Range)	\pm 1.5%
Capacitance	60mF (Auto Range)	\pm 3.0%
Frequency	60MHz (Auto Range)	\pm 1.5%
Duty Cycle	10~95%	\pm 2.0%
Transistor hFE	Yes	
Diode	Yes	
Continuity	Yes	
NC AC Voltage Detector	90-1000V	

