

DIGITAL LCR METER LCR4070

APPLICATION: This is a Digital LCR Meter with Inductance, Resistance, Capacitance & Continuity Measurement

FEATURES:

- Display: LCD Display with Backlight
- Zero Adjustment Key.
- Low battery indication
- Fuse Protection.
- Backlight Shut down after 7 Sec.
- Power: 9V X 1 battery
- Operation Temperature & Humidity: 25 °C, RH. <75%.
- Display Size: 64 X 35 mm.
- Unit Size: 185 X 90 X 53 mm.
- Weight: Approx. 380g (Including Battery)
- Accessory: Instruction Manual, 1 Set of Test Leads, 1 Pc 9V Battery



SPECIFICATION:

Functions	Ranges	Best Accuracy
Inductance	2 mH, 20mH, 200mH	± 2%
	2H, 20H	± 5%
Capacitance	2nf - 100mf (Auto Range)	± 3 %
Resistance	0Ω – 200mΩ	± 1.5%
Continuity	Buzzer Sounds Upto 30Ω	