

DIGITAL LUX METER LX102

APPLICATION: This is 3½ Digits 1999 Counts, light meter is applied for Architecture, Photography work, Houseplant, Offices and Places where you want to use it to get Optimum Light.

FEATURES:

- Measuring parameters lux FC
- Sensor type silicon photodiode
- Low battery Indication
- Data hold function
- MAX /MIN Test
- Auto power Off: After 10 min from last key operation
- Operating Temperature & Humidity: 0°C To 40°C, 45~80%RH
- Storage Temperature & Humidity: -20°C To 60°C, 45~80%RH
- Power supply: 9 Volt Battery
- Weight: 120 gms
- Display Size: 30 x25mm
- Unit size: 192 x 53.8 x 35mm
- Accessories: Instruction Manual, 1 pc 9V Battery, Carrying Pouch

SPECIFICATION:

Measuring Range-0~200000 Lux

0~20000 Lux FC

ACCURACY- 4~6%

