

## DIGITAL TRUE RMS MULTIMETER DT108

**APPLICATION:** This is a 3½ Digits True RMS multimeter with Backlight. This instrument can be used to measure AC/DC voltage, AC/DC current, Resistance, Frequency, Non-Contact Voltage detection and other parameters. It is an ideal tool for the Electricians, Engineers, Laptop & Mobiles & Electronics appliances Repairing Centre, Factories, Industries, Laboratories, Students, Household.

### FEATURES:

- Display: 3½ Digits with 2000 Counts with Backlight.
- Over Range Indication, Torch
- Overload Protection
- Fuse Protection
- Wall Mount & Table Type
- Data Hold Function
- Auto/Manual Ranging
- Non-Contact AC Voltage Detector. (NCV)
- Sampling Time 0.4 Seconds
- Auto Power off: 15 mins.
- Operating Temperature & Humidity: 0°C To 40°C, 45%-80%RH
- Storage Temperature & Humidity: -20°C To 60°C, 45%-80%RH
- Power supply: 2 X AAA Batteries.
- Display Size: 47 X 30 mm
- Unit Size: 148×69×44mm
- Weight: 180gm Excluding Battery
- Accessories: Instruction Manual, 2 X AAA Batteries, 1Set Test lead.



### SPECIFICATION:

Basic Function	Range	Best Accuracy
AC Current	200μA/20mA/200mA/10A	±3%
DC Current	200μA/20mA/200mA/10A	±2.0%
AC Voltage	200mV/2V/20V/200V/600V	±1.5%
DC Voltage	200mV/2V/20V/200V/600V	±0.5%
Resistance	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/20MΩ	±1.5%
Frequency	99.99 MHz	±0.5%
Diode & Continuity	Yes	
NCV	Yes	