



R-100 RESISTANCE DECADE BOX

A precision instrument that allows users to manually select specific resistance values for use in testing, calibration, and circuit prototyping. It's an essential tool in electronics labs, service centers, and educational settings.

The R-100 offers seven Decade ranges of Resistance for product design or calibration check applications with heavy duty, durable construction and separate grounding terminal.

Offers three binding posts permit isolated substitutions, 1% Resistance substitution from 1 to 11,111,110½ and values can be changed in 1½ increments.

Features 0.3W resistors and 0.3½ internal zero resistance.

SPECIFICATIONS

Resistance Ranges	1 to 11,111,111Ω in 1Ω steps
Internal Resistance	Approx. 0.3Ω
Power	0.3W Resistors
Connection	Three (3) binding post
Accuracy	1%
140mm×130mm×48mm	140mm×130mm×30mm
260g	295g



Contact:

CEM INSTRUMENTS (INDIA) PVT. LTD.
32A, Ganesh Chandra Avenue, 4th Floor
Kolkata 700013
Email: cem@metravi.com